

WISEASY QS

QR Payment Speaker



4G Network



High power
loudspeaker



Powerful battery



Strong
compatibility



Broadcasting on the code

With the aggregate code sticker, after the successful accepting of payments, QS broadcasts the amount of money received immediately, effectively eliminating missing or losing of orders.

Breaking through the noise with a loud speaker

High sound volume and high power. Up to 110 dB speaker allows volume adjustments based on the application scenarios. Even in a noisy environment, the details of each collection can be heard clearly.

A speaker of dual use, the top billboard maximizes the advertising effects

Pluggable acrylic panel can be customized in shapes and sizes, and used to display advertising or marketing contents.

4G network brings ubiquitous coverage

No plug in, and no winding, 4G networks bring secured signal stability, allowing for faster and more accurate broadcasting of each collection.

Super capacity battery for 400 hours standby!

2500 mAh large battery, 400 hours of extra long standby time to meet the full day use requirements.

Unlimited application possibilities in various scenarios

With an open and neutral message system, QS focuses on real-time message broadcast. In addition to the payment collection scenario, it brings unlimited application possibilities in various scenarios.

Technical Specifications



Platform
UNISOC8910



CPU
500MHz



Memory
1M RAM + 2M ROM



Indicator
1* Charging indicator,
1* Device status indicator



Speaker
3W



Network
2G/4G



Audio
mp3, WAV, PCM audio files



Mic
Optional



OTA
Support OTA update



SIM slot
Micro SIM card, 12*15,
(optional ESIM)



Key
Power key, Volume up/down
Key, Reset Key



Battery
3.7V/2500mAh



USB Port
TypeC port,
support Charging, 500mAh



Charger
5V/1A



Charging line
Available



Dimensions
82*77*26mm



Temperature
Storage temperature: -35°C to 70°C
Operating temperature: -10°C to 55°C
Humidity: ≤95%